

CYANSKY  
赛思铠

L2  
轻量化越野跑头灯

说明书

产品参数

模式	主灯照明				副灯照明	
档位	低亮	中亮	高亮	极亮	红光变亮	红光闪烁
亮度(流明)	30	150	450	1300	10	10
续航(小时)	48	20	8	2	50	100
射程(米)	25	65	98	176	/	/
发光强度(坎德拉)	156	1056	2401	7744	/	/
防撞厚度	2米					
防水等级	IP68(水下2米)					
尺寸	99*36*44.毫米					
重量	整机+配件110g					
工作温度	-30℃~50℃/-22℉~122℉					

注：以上数据根据ANSI / PLATO FL1标准，使用一节CYANSKY 3400mAh锂电池在25℃±2℃、湿度50%-80%的环境下，于CYANSKY实验室环境中测试所得数据，实际使用中可能因电池及使用环境改变而改变。

综合续航时间为产品电路智能续航测试的累计续航时间总长。

包装清单

L2头灯（含支架、灯带）、绝缘片、1\*BL1834电池、防水圈、充电线、说明书、吊带、保修卡。

认证

CE、WEEE、FCC、RoHS2.0、UKCA、海运/空运运输鉴定报告。

放电曲线

使用说明

**开/关机:**  
长按开关0.5秒开机/关机，开机进入记忆档位。（极亮档不在记忆档位中）

**改变亮度：**  
单击开关调节亮度（低->中->高循环），双击开启极亮档。

**红光模式：**  
长按按键1.2秒，切换到红光模式，单击切换红光常亮、闪烁。

**锁定和解锁：**  
快速四击开关，此时红灯闪烁两次并熄灭，代表头灯进入锁定状态；

**锁定状态下，以下两种方式均可解锁：**  
1：快速四击开解锁键；  
2：连接充电线。头灯自动解锁（充电解锁方式头灯不会闪烁）；

充电操作：

翻开充电口保护帽，将接通电源的充电线插入Type-C充电口，充电时显示红灯，充满显示绿灯，5V/2A电流充电，2.5小时左右充满；充满后按下充电线，盖上USB保护帽，避免异物或液体进入。充电时可以开启主灯。

电量显示：

关机状态单击按键/开机显示电量，电量指示灯3秒后熄灭（电池电压高于4.5V电量指示灯不亮）。  
电量在80%以上显示绿灯；  
电量在50%-80%，绿灯闪烁；  
电量在20%-50%之间，显示红灯；  
电量在20%以下，红灯闪烁，提示电量不足。

低电量提示：

电量不足时，电量指示灯红灯以每秒钟闪烁3次持续闪烁，当前工作的LED灯每3分钟闪烁三次，提示更换电池或者充电。

低电降档：

检测到电池电压低于3.0V，主白光灯光点亮后会逐步自动降低当前工作档位，直到降低到低亮档。头灯在电池电压降低到2.8V时自动关机。

限时保护：

产品极亮档具有限时保护设计，在极亮档工作时，1300流明亮度下工作1分钟左右，会逐渐降低到1000流明左右，然后会根据温度安全性来调节亮度。

温控保护：

产品温度高于安全值，会通过温控降低产品亮度，以避免产品损坏和伤及用户，当温度降低到低于安全值后，产品亮度会逐渐上升。

支架角度调节：

支架可以向上下向下调节各90度角；实现180度角度调节。

温馨提示：

携带不用时将电池盖旋松半圈，让产品断电，避免在携带时误点亮。  
如果在携带中误点亮，会耗掉电能，同时也可能会因产品发热而烧坏头灯周围物体。

注意事项

- 请在产品放置不用时取出电池；
- 儿童须在成人的监督下使用本产品；
- 产品亮度高，请勿直视，否则会造成眼睛伤害和短暂失明；
- 请勿将装有电池的 product 投入火中，否则会引发爆炸；
- 请勿将打开电池盖或USB盖的产品投入水中；
- 请勿将电池的正负极短接。
- 请勿将带电池的 product 放入微波炉内，否则会发生爆炸。

保修条款

\*灯具产品自售出之日起15天内，在正常使用情况下，出现产品质量问题，客户可选择更换新品，所换产品应为同型号同规格的新品；如同型号同规格的产品停止生产时，则调换不低于原产品性能的同品牌同类产品。



· 5年免费保修期：灯具产品自售出之日起5年内（电池1年内），用户在正常使用情况下，出现产品质量问题，则享受免费维修服务。5年后可以进行有偿维修，只收取成本费。

· 消费者保时充（保修卡）、购物发票或截图网上购物时零售商提供的号码与经销商联系，由经销商对消费者提供服务，我公司将对经销商提供服务支持。

· 保修服务不包括由于以下原因造成的任何损坏或故障：  
1. 过高掉落、擅自拆卸或改造；  
2. 使用、存放或维护不当；  
3. 电池漏液；  
4. 盐水和腐蚀性环境机组；  
5. 维护不当造成的损坏；  
6. 普通磨损/褪色。

东莞市亦明电子有限公司

网站: http://www.cyanskylight.com  
邮箱: cs@cyanskylight.com  
电话: 0769-82829209  
地址: 广东省东莞市大岭山镇白泥山中路7号向东南科  
科技园2号楼6楼

# L2

## Rechargeable Lightweight Trail Running Headlamp

### User Manual

FLI STANDARD	Main Light				Secondary Light	
	LOW	MED	HIGH	TURBO	Red	Red Flash
ON/TIME/Lumens	30	150	450	1300	10	10
PUNTIME/Hours	48	20	8	2	50	100
DISTANCE/Inches	25	65	98	176	1	1
INTERVIEW/Inches	155	555	2401	7744	1	1
IMPACT RESISTANCE	2M					
WATERPROOF	IP68 (2 meters underwater)					
SIZE	69.4" x 1.5" x 34mm					
WEIGHT	110g(battery and accessories included)					
WORKING TEMPERATURE	-30°C ~ 50°C / -22°F ~ 122°F					

Note: The above data is based on the ANSI FLA F1 standard. The data was obtained from testing in the CYANSKY laboratory environment using a CYANSKY 3400mAh lithium battery at 25°C ±2°C and 50%-80% humidity. Actual usage may vary due to battery and environmental changes. The comprehensive endurance time is the cumulative endurance time obtained from intelligent downshifting testing of the product circuit.

#### Included

L2 Headlamp (including bracket and light strip), insulating sheet, 1 BL1834 lithium battery, waterproof ring, charging cable, user manual, hanging tag, warranty card.

#### Certification

CE, WEEE, FCC, RoHS 2.0, UKCA, sea/air safe transport.

#### Operating Instruction

**Power on/off:**  
Press and hold the button for 0.5 seconds to turn on/off the headlamp. The headlamp will turn on to the memorized mode. (Turbo mode is not included in the memory settings.)

**Adjust brightness:**  
Single-click the button to adjust brightness (low-medium-high cycle). Double-click to TURBO mode.

**Red light Modes:**  
Long press the button for 1.2 seconds to switch to red light mode, and single-click to switch between constant red light and flashing.

**Lock and Unlock:**  
Quickly tap the button four times. At this time, the red light flashes twice and goes out, indicating that the headlamp is in the locked state.

In the locked state, the following two methods can unlock:  
1. Quick quadruple tap to unlock switch.  
2. Connect the charging cable, the headlamp will unlock automatically (the charging unlocking method will not cause the headlamp to flash).

#### 18650 3400mAh Lithium Battery

**LOW:** ..... 48 Hours  
**MED:** - - - - - 20Hours  
**HIGH:** ——— 8 Hours  
**TURBO:** ===== 2 Hours

**Battery Level Display:**  
When the battery is turned off, click the button to display the battery capacity. The battery indicator light will go out after 3 seconds (when the battery voltage is higher than 4.5V, the battery indicator light will not light up).  
The green light is displayed when the battery level is above 80%.  
The green light flashes between 50% and 80%.  
The red light is displayed between 20% and 50%.  
The red light flashes when the battery level is below 20%, indicating low battery.

**Low Battery Warning:**  
When the battery is low, the battery level indicator flashes red three times per second continuously, and the LED light currently in operation flashes three times every 3 minutes, indicating that the battery needs to be replaced or charged.

**Low Battery Downshift:**  
Detected battery voltage below 3.0V. Under the main white light mode, the current working level will gradually decrease automatically until it reaches the low brightness level. The headlamp will automatically shut down when the battery voltage drops to 2.8V.

**Time-limited Protection:**  
The extreme brightness mode of the product is designed with time-limited protection. When working in extreme brightness mode at a brightness of 1300 lumens, it will gradually decrease to around 1000 lumens after about 1 minute of operation, and then adjust the brightness according to temperature safety.

**Temperature Control Protection:**  
When the product temperature exceeds the safe value, it will lower the brightness through temperature control to avoid damage to the product and harm to the user. When the temperature drops below the safe value, the brightness of the product will gradually increase.


**Reminder:**  
Please loosen the battery cover half a turn to cut off the power to avoid accidental illumination during carrying. If accidentally illuminated during carrying, it will consume energy and may burn surrounding objects due to product heating.

#### Caution

Please remove the battery when the product is not in use. Children should use this product under the supervision of adults. Do not stare directly at the high brightness of the product, as it may cause eye damage and temporary blindness.  
Do not throw the product with batteries into the fire, as it may cause an explosion.  
Do not immerse the product with opened battery cover or USB cover in water.  
Do not short-circuit the positive and negative poles of the battery.  
Do not put the product with batteries into the microwave oven, as it may cause an explosion.

#### Warranty Terms

For the first 15 days from the date of sale, if there is a product quality problem under normal use, customers can choose to replace it with a new product of the same model and specification. If the product of the same model and specification has been discontinued, it will be replaced with a product of the same brand and class with not lower performance.  
5-year free warranty period: From the date of sale, the lamp product has a free warranty period of 5 years (1 year for batteries). If there is a product quality problem under normal use, the user can enjoy free repair service. After 5 years, paid repair service will be provided, only cost fees will be charged.  
When consumers seek warranty service, they should contact the dealer with the "Warranty Card", shopping invoice or receipt, or the code provided by the online retailer, and the dealer will provide service to the customer. Our company will provide service support to the dealer.



## CYANSKYLIGHT CO., LTD

Web: <https://www.cyanskylight.com>  
Email: [info@cyanskylight.com](mailto:info@cyanskylight.com)  
Tel: +86-769-82829209  
Address: 601, 2# Building, Xiangdong Technopark, 7# Bainian Middle Road, Dalingshan Town, Dongguan, 523000, China

